

VADDIO™/SONY® JOYSTICK CONTROL BUNDLE

For Vaddio Cameras and Control Systems

The Sony Remote Control Joystick can control all camera settings including the Pan/Tilt/Zoom functions and six presets patterns. The ergonomic joystick and feature rich control panel provide superb operability in various remote-shooting applications (Figure 1).



Figure 1:
Sony RM-BR300
Joystick Remote Control Unit

Vaddio/Sony Joystick Control Bundle Includes:

- Sony Joystick Remote Control Unit
- Custom 20' (6.1m) VISCA Cable (8-Pin mini din to DB-9M)
- Custom 20' (6.1m) ControlVIEW Xtreme Link Cable (9-pin Phoenix Type to DB-25M) for tally contact output
- Power Supply
- AC Cable (North America or Euro)

Key Product Features:

- Joystick can control up to seven VISCA based PTZ cameras (daisy chained control configuration only - Figure 2).
- Preset memory supports up to 16 combinations of settings (EVI-D100, EVI-D70 and BRC-300 have only 6 presets per camera), including camera position, zoom, focus and backlight can be stored in the memory of the camera using this unit.
- An external video switcher with the contact control interface can be used to switch between different camera video sources (contact closure)
- RS-232 or RS-422 communication interfaces
- Control of brightness, white balance, focus (auto/manual)

Table 1:
Vaddio/Sony Joystick Control Bundle – General Specifications

Vaddio/Sony Joystick Bundle Part #s	NTSC – 999-6605-000 PAL – 999-6605-001
Camera Control Interface	RS-232C (VISCA protocol) / RS-422 (VISCA protocol)
External control	Contact Closure (tally contacts)
Power requirement	DC 10.8 to 13.2 V
Power consumption	2.4 W
Compatible Cameras	All Vaddio VISCA Control Camera Packages Sony EVI-D100, EVI-D70, BRC-300
Maximum Number of Controllable Cameras	Seven Cameras – Daisy Chain Only
Dimensions (W x H x D)	15-1/2" x 7-3/8" x 5-3/4" 39.13cm x 18.5cm x 14.59cm
Weight	2 lb - 1 oz 950 g

Figure 2:
Sony RM-BR300 Joystick with Daisy Chain Control

